

- Supported models HP-21, HP-22, HP-25C, HP-27, HP-29C
- Continuous Memory storage for all models - requires no battery power
- Storage: HP-25C, 207 program files. HP29C, 360 files, either program or data
- Continuous memory has reset
- Internal USB battery charger with charge indicator, can run calculator as well
- LiPo battery powered
- Selectable low battery reference
- Constant current LED driver
- Text editor for creating names for stored programs
- Turbo Mode, fast code execution
- Decimal/Binary/Hex/Octal convertor
- Least fraction calculator
- Option to display program text instead of original key numbers
- Real time clock with alarm, +/- 5 PPM, can be set to view at switch on
- Separate count up and count down timers with alarm
- Selectable DDMMYY, MMDDYY, YYMMDD or Text date format
- Clock display in numeric or text format - 5 Past 3, 29 to 11, Noon, etc
- Menu activated right switch (in case user's model does not have one)
- Selectable key de-bounce
- Beeper - selectable Off, Loud or Soft
- Display setting – Bright or Dim
- Sleep Function
- 29C printer interface via Bluetooth link to PC - NRM or TRC modes, font is same as 97
- Power on model display
- Temperature display

- Battery voltage display
- Version display
- 3 extra programmable functions for the HP-25C
 - Beep
 - GSB 49
 - RTN
- 6 extra programmable functions for the HP-29C
 - Random Number
 - Constants
 - Beep
 - Data Swap
 - File access - load programs or load/save data files (similar to 67/97)
 - Notes Display
- 2 inbuilt games, Tetris and 21 with music and sound effects